## **AMENDMENT**

## MORTAL KOMBAT Kit, using the T-Unit CPU

This amendment updates the Mortal Kombat Manual. Please place this information in the manual.

Page: 1-2

**Notice: Power Supply** 

Be sure the power supply from your old game is capable of +5V dc at 5A and +12V dc at 2A.

Page: 2-2, 2-3

A-14816-43725; CPU Board Assembly:

Surface mount parts were not previously marked.


Part Number 5410-12862-00 5340-13321-00 **Part Desiginator UE13** 


UA11-UA14.

UB11-UB14

Description IC, DMA2

IC, 48121, 80nsec





Page: 2-4, 2-5, 2-6

A-14732-40025 and A-14732-43725; Sound Board Assembly

Surface mount parts were not previously marked.

Part Number

**Part Desiginator** 

Description

5433-12962-00

IC, OKI6295, 4 Channel



Page: 3-4

Typical Cabinet Wiring

The connector P3 on the CPU should changed to the following.

1 Blue +Speaker 2 Violet - Speaker 3 +12V Gray-Yellow **P3** +12V 4 Gray-Yellow 5 Key 6 NC 7 Ground Black 8 Gray +5V 9 Black Ground To Sound Board

Page: Inside Back Cover **CPU Board Jumper Chart** Jumper values changed.

Designator	<u>Value</u>
J18, J19, J22, J24, J28	$0\Omega$ (jumper)
R154	$0\Omega$ (jumper)
J100, J101	$47\Omega$
R156	$68\Omega$
R165	$39\Omega$