OPERATOR'S MANUAL

EXCEISIOR.





BREAK THROUGH THE COVERS THAT HIDE THE AMAZING SEXY GIRLS OF EXCELSIOR










• Photo screen with 256 colours (512x512 photos, 1/2 zoom)

• Horizontal screen • Six fantastic scenarios

P C B CONECTOR JAMMA

SOLDER SIDE	PIN	NO.	COMPONENTS SIDE
GND	Α	1	GND
GND	В	2	GND
+5V	С	3	+5V
+5V	D	4	+5V
	Е	5	
+12V	F	6	+12V
	Н	7	
COIN COUNTER 2	J	8	COIN COUNTER 1
COIN LOCKOUT 2	K	9	COIN LOCKOUT 1
SPEAKER (-)	L	10	SPEAKER (+)
	M	11	
GREEN	N	12	RED
SYNC	Р	13	BLUE
SERVICE	R	14	VIDEO GND
	S	15	
COIN IN 2	Т	16	COIN IN 1
2P START	U	17	1P START
2P UP	٧	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	X	20	1P LEFT
2P RIGHT	Υ	21	1P RIGHT
2P FIRE	Z	22	1P FIRE
2P WORK	a	23	1P WORK
2P BOMB	b	24	1P BOMB
	С	25	
	d	26	
GND	е	27	GND
GND	f	28	GND

CONTROL PANEL










fire

work

bomb



ITEM	DESCRIPTION	DIP SWITCH 1								
		1	2	3	4	5	6	7	8	
COIN MODE A B	COMMOI EACH Of		OFF ON							
MODE A COIN/CREDIT	1 COIN 2 COIN 3 COIN 4 COIN 5 COIN 6 COIN 1 COIN 1 COIN 1 COIN 2 COIN 3 COIN 5 COIN 8 COIN	1 PLAY 1 PLAY 1 PLAY 1 PLAY 1 PLAY 1 PLAY 2 PLAY 3 PLAY 5 PLAY 6 PLAY 3 PLAY 2 PLAY 3 PLAY 3 PLAY		OFF ON OFF	OFF ON OFF ON OFF ON OFF ON ON OFF ON OFF ON OFF ON OFF ON ON	OFF OFF ON ON ON OFF OFF OFF OFF ON ON ON	OFF OFF OFF OFF OFF OFF ON ON ON ON ON ON ON			
MODE B COIN IN 1	1 COIN 2 COIN 3 COIN 5 COIN	1 PLAY 1 PLAY 1 PLAY 1 PLAY		OFF ON OFF ON	OFF OFF ON ON					
MODE B COIN IN 2	1 COIN 1 COIN 1 COIN 1 COIN	2 PLAY 3 PLAY 5 PLAY 6 PLAY				OFF ON OFF ON	OFF OFF ON ON			
CREDITS FOR START	1 2							OFF ON		
PERCENTAGE	80° 90°								OFF ON	
TEST MODE	NC YE									OF ON

ITEM	DESCRIPTION	DIP SWITCH 2								
		1	2	3	4	5	6	7	8	
NUMBER OF LIVES	3 2 4 1	OFF ON OFF ON	OFF OFF ON ON							
CENSURE	TOTAL PARTIAL EXCLUDED EXCLUDED			OFF ON OFF ON	OFF OFF ON ON			24		
DIFFICULTY	NORMAL EASY HARD VERY HARD			-		OFF ON OFF ON	OFF OFF ON ON		2	
CONTINUE PLAY	YES NO							OFF ON		
DEMO SOUND	NO YES								OFF ON	

